

INSTALLATION SHEET

Model: NA06-ES-8

MAIN FEATUERS:

- Microwave sensor and emergency function
- High quality construction with High lumen SMD LED
- CRI>80,PF>0.9 LED driver
- 3 hours emergency time when power cut
- Up to 70% energy saving compared to standard CFL
- Long lifetime of 50,000 hours
- No UV/IR light
- Environment friendly, without Mercury or any other hazardous substance



Corridor Function:

- When the sensor detects movement, the light will operate at 100%.
- When the sensor stops detecting any movement, it will dim down to 10% of the normal output.
- The corridor function will not work whilst in emergency mode

PARAMETERS:

Input Voltage	AC85-265V,50~60Hz
Battery Back up	9.6V/1000mAh NI-CD
Rated Power	8W
Warranty	3 years
Lamp Body Material	Anti-UV PC
Size	D230*H90mm
Function	STD/ON-OFF/EM
Color Temperature	Tri-color(3000K/5000K/6000K)
Emergency Wattage	3W
Emergency time	180mins
Sensor distance	5-8m
Time Delay(adjustable)	3-240s
Package	Standard pack or Color Box
Custom service	OEM/ODM service
Feature	IP65 Waterproof

CUSTOMIZED

Pattern Design	Available, Please send us your design artwork
LOGO Printing	Available on Packaging box, or sticker on the product
Packaging include	1pc*led emergency light
Packaging	10pcs per carton, carton size: 42*28*52cm, carton weight: 11/12kg

INSTALLATION:

Step1: Isolate mains power supply

Step2: Follow the wiring instructions below

L1 – Un-switched Live for Permanent Emergency Module Supply

N – Neutral

E – Earth (optional for continuity only)

L – Switched Live for Normal Operation (only connect for maintained use)

Step3: Open the mains power, Lights on the LED lamp switch on/off to control lights. Check the emergency function, Green LED indicator is on that shows all are working well. Cut off the main supply, led lamp switch to emergency output immediately.

NOTICE:

When using electrical equipment, basic safety precautions should always be followed including the following:

- Before commencing installation or servicing, turn off and isolate the circuit to be worked on by removing the fuse or switching the circuit breaker off at the distribution board.
 - This product is suitable for connection to a 85-265Vac 50/60Hz supply.
- The emergency fitting is not suitable for use on a battery supply, trickle or intermittent re-charging circuit.
- The emergency fitting is not protected against supply voltage polarity reversal.
- The recharging device will recharge the battery normally after removal of a battery short-circuit.
- When cutting holes, drilling or screwing take care not to damage existing wiring or pipework.

STORAGE:

If the emergency light is not used for over 3 months, it should be connected to AC power for full charging and discharging (until LED lamp is completely off). Then keeping the emergency driver on main power for 24 hours and put it in dry ventilated place.



The Waste Electrical & Electronic Equipments regulations (WEEE) requires that products bearing this symbol must not be disposed of with household waste as they may contain substances harmful to the environment. The local authority can provide advice on recycling.