

## INSTALLATION SHEET

Thank you for using our led emergency twin spot lights. This Double Head Led Emergency Light is recommended for Commercial Lighting Fixture widely use in Hotel, Office, Public Buildings, Apartment Buildings, shopping mall, etc. Which can be used as emergency lighting in the case of electric outage. These instructions should be read carefully & retained after installation for future reference & maintenance.



### INSTRUCTION

#### Model: NA07-TS-42

- This Twin Emergency Spotlight will provide lighting to safely exit a building in case of a fire or power cut. With a backup battery that lasts up to 3 hours and powered by LED that lasts for 25,000 hours this emergency light will provide ample light and complies with British Fire and Safety Regulations.
- Fast efficient installation. Simply put the AC wire through the cable cover, connect the L/N and Earth feeds into the quick-fit screwless terminal block.
- This emergency light can be used in a variety of public places and settings, from schools to warehouses or offices to hospitals.
- Upgrade to LED now to keep your workplace safe whilst saving money on electricity bills and reduced replacement costs.

### SPECIFICATION

Input Voltage	85-265V/50-60HZ	Battery Type	3.6V/4500mAh Ni-Cd
Emergency Output Power	2*8W	Dimension	31*11*33.5cm
Emergency time	180mins	Protection Grade	IP65
Emergency Conversion Time	<5S	Charging time	24hours
Working Temperature	-10~50°C	Warranty	2 years

### INSTALLATION

Step1: Isolate mains power supply

Step2: Follow the wiring instructions below

L1 – Un-switched Live for Permanent Emergency Module Supply

N – Neutral

E – Earth (optional for continuity only)

L – Switched Live for Normal Operation (only connect for maintained use)

Step3: Ensure that all electrical connections are firm with no loose strands and secure the cable with the anchor provided.

Step4: Open the mains power, Lights on the LED lamp switch on/off to control lights. Check the emergency function, cut off the main supply, led lamp switch to emergency output immediately.

**INDICATOR:**

Green LED indicator is on that shows main power is on, when emergency function, green light is off;

**CUSTOMIZED**

Pattern Design	Available, please send us your design artwork
LOGO Printing	Available on Packaging box, or sticker on the product
Packaging	10pcs per carton, carton size: 32*32*40cm, carton weight: 9/10kg

**NOTICE:**

When using electrical equipment, basic safety precautions should always be followed including the following:

- Before commencing installation or servicing, turn off and isolate the circuit to be worked on by removing the fuse or switching the circuit breaker off at the distribution board.
- This product is suitable for connection to a 85-265Vac 50/60Hz supply.
- The emergency fitting is not suitable for use on a battery supply, trickle or intermittent re-charging circuit.
- The emergency fitting is not protected against supply voltage polarity reversal.
- The recharging device will recharge the battery normally after removal of a battery short-circuit.
- When cutting holes, drilling or screwing take care not to damage existing wiring or pipework.

**STORAGE:**

If the emergency light is not used for over 3 months, it should be connected to AC power for full charging and discharging (until LED lamp is completely off). Then keeping the emergency driver on main power for 24 hours and put it in dry ventilated place.



The Waste Electrical & Electronic Equipments regulations (WEEE) requires that products bearing this symbol must not be disposed of with household waste as they may contain substances harmful to the environment. The local authority can provide advice on recycling.