

Power capacitors application solution for induct furnace / switch on and off / welding machine power supply

RFM series, super audio water-cooled electric capacitance

Function and Application:

To be applied for A/c harmonic voltage ≤4.0KV, Frequency <50KHz induct heat power supply, To provide reactive power capacitive current

current
The technology unique point:

The whole film oil-immersed structure NO PCB

- ■Single water/grouping scheme can be customized
- ■The outlet temperature of the cooling
- water to pure water, < 40 $^{\circ}$ C

Conditions of use/technical para meters/product standards

Temperature range: 25 $^{\circ}$ C ~ + 50 $^{\circ}$ C

The outlet temperature of the cooling

water to pure water,< 40 °C

Rated voltage UN: 1 ~ 4.0 KV

Rated frequency FN: < 50 KHZ

QN the rated capacity: 500 ~ 2000 kar

The maximum current:≤1000A

Product standards: IEC60110-1 (1998)

GB/T3984.1-2004 (also can be made according to


customer standard)
Specification:



<u> </u>	/11,										
$\mathbf{RAM} \ \mathbf{U}_{N} - \!$											
Туре	Rated voltage: U UN • KV	Nominal capacity: QN•Kar	Rated frequency FN • KHz	Rated capacita nce: CN • uF	Rated current IN•A	L mm	W mm	H mm	Group	Note	
RFM3. 0-500-15S	3.0	500	15	0. 59	167	303	122	165	NO		
RFM4. 0-1050-35S	4.0	1050	35	0. 298	263	303	122	165	NO		
RFM ₃ 3. 0-500-30S	3.0	500	30	0. 295	167	240	125	150	NO		
RFM3. 0-560-25S	3. 0	560	25	0. 396	187	303	122	165	NO		

Туре	Rated voltage:U UN•KV	Nominal capacity: QN • Kar	Rated frequency FN • KHz	Rated capacita nce: CN•uF	Rated current IN•A	L mm	W mm	H mm	Gro up	Note
RFM3. 0-680-20S	3.0	680	20	0. 601	227	303	122	165	NO	
RFM4. 0-694-23S	4.0	694	23	0. 300	174	240	125	150	NO	
RFM4. 0-700-30S	4.0	700	30	0. 232	175	303	122	165	NO	
RFM4. 0-750-25S	4.0	750	25	0. 298	189	303	122	165	NO	
RFM4. 0-804-20S	4.0	804	20	0.400	201	285	125	170	NO	

Product schematic diagram (Three view drawing):



Tel: +86-514-87782298, 87782296 E-mail:positioning@china.com; FAX:+86-514-87782297, 87367519 WEBSITE: http://www.pst888.com